



DATA SHEET

ROOM SOLUTION: ROOMMATE + TAP IP

Make video collaboration easier for employees and IT by adding Logitech RoomMate and Logitech Tap IP to any meeting space with an existing Logitech conference camera.

RoomMate and Tap IP eliminate the need for an additional, dedicated computer in the room. Together they allow employees to join a meeting with just one touch.

TURN ANY SPACE INTO AN APPLIANCE-BASED VIDEO CONFERENCING ROOM

Add RoomMate to an existing Logitech MeetUp, Rally, or Rally Plus camera and turn any space into an appliance-based video conferencing room, with a compact form factor that can be mounted out of sight and out of harm's way.

Configure the room for leading video conferencing platforms, including Microsoft Teams Rooms on Android, Zoom Rooms, RingCentral, and others*. Add to an existing Logitech MeetUp, Rally, or Rally Plus camera to create a complete appliance room solution.

PRODUCT FEATURES & ACCESSORIES

PRODUCT FEATURES

POWER, WITH CONNECTIONS

With its sleek, low-profile form factor, Logitech RoomMate delivers all the processing power you need for HD video conferencing in rooms with one or two displays.

START MEETINGS WITH A TAP

Meetings begin with just one touch with Logitech Tap IP, a network-connected touch controller that's easy to use and simple to set up.

VERIFIED AUDIO PARTNERS

Use the audio system of your choice. Default to the conference camera's audio when you pair RoomMate with MeetUp or a Rally system. Or choose a verified audio system from our partners, such as QSC, Shure, and Biamp, when RoomMate is used alongside Rally Camera.

FLEXIBLE MOUNTING

Attach Logitech RoomMate anywhere in your meeting space using Compute Mount with cable retention and a hideaway design for a tidy installation.

DEVICE MANAGEMENT AND INSIGHTS

Monitor, manage, and get business insights into how your rooms are being used with Logitech Sync. Monitor and manage your meeting room devices from the Zoom Device Manager.

CLEAN AND SECURE CABLING

Streamline setup for Logitech Tap IP with a single PoE cable, and keep connections tight with built-in strain relief and retention mechanisms.

RECOMMENDED ACCESSORIES



Tap Riser Mount

Elevated table mount with swivel and cable management



Tap Wall Mount

Space-saving wall mount with cable management



Tap Table Mount

Swiveling table mount with cable management



Tap Scheduler

Purpose-built scheduling panel for meeting rooms



Scribe

Effortlessly share whiteboards into video meetings with Logitech Scribe, an AI-powered whiteboard camera



Swytch

Connect a laptop to a room system's AV equipment for use with any video meeting or webinar.

PRODUCT SPECS & LINKS

TAP IP		ROOMMATE		WARRANTY	
<p>Touch Screen: 257 mm (10.1 in) diagonal screen with 14° display angle</p> <p>Resolution: 1280 x 800</p> <p>Cabling: Power over Ethernet (PoE) cable (not included), IEEE 802.3af Type 1, Class 3 device</p> <p>Cable Management: Internal cable retention and strain relief system</p> <p>Ethernet: 10/100mbps</p> <p>Wi-Fi: 802.11a/b/g/n/ac</p> <p>Device Management: Logitech Sync</p> <p>Color: Graphite</p> <p>Mounting: 100 mm x 100 mm VESA FDMI</p> <p>Dimensions (H x W x D): 58 mm (2.3 in) x 244 mm (9.6 in) x 179 mm (7.0 in)</p>		<p>Operating System: Logitech CollabOS 1.4 or higher</p> <p>Device Management: Logitech Sync and supported device management platforms</p> <p>Certified Hardware: Logitech MeetUp, Rally Camera, Rally System, Rally Plus System, Tap, Tap IP</p> <p>Verified Hardware: Biamp TesiraFORTÉ X 400, QSC Q-SYS Core 8 Flex, Shure IntelliMix P300. For latest information on compatible products, contact your preferred partner.</p> <p>Network Protocol Support: IPv4, IPv6</p> <p>Proxy Support: IP based Proxy, FQDN based Proxy, Proxy using PAC file</p> <p>Interfaces</p> <ul style="list-style-type: none"> HDMI Out: 2 HDMI In: 1 USB: 3x Type A <p>Network: 10/100/1G Ethernet</p> <p>WiFi: 802.11a/b/g/n/ac</p> <p>Operating Voltage/Power: 100-240V, 19V, 4.74A</p> <p>Full Disk Encryption: AES-128</p> <p>Data Encryption: Symmetric Keys, PKI</p> <p>Device Identity: Protected by device attestation</p> <p>Device Access: Authenticated using API</p> <p>Key Protection: Arm TrustZone, RPMP</p> <p>Device Security: Kensington Lock</p> <p>Color: White</p> <p>Dimensions (H x W x D): 34.5 mm (1.36 in) x 161 mm (6.34 in) x 211 mm (8.31 in)</p>		<p>Standard: 2-year limited hardware warranty included</p> <p>Extended: 1-year and 3-year extended warranties available at the time of hardware purchase. Contact your reseller for availability.</p>	
				<p>*CERTIFICATIONS & COMPATIBILITY</p> <p>Appliance Mode</p> <p>Supports compatible video conferencing software including Microsoft Teams Rooms on Android, Zoom Rooms, RingCentral Meetings Rooms. Contact Logitech or see https://prosupport.logi.com/hc/en-us/articles/1500001344641 for availability information and additional video conferencing platforms.</p> <p>Certifications</p> <p>All components included in the room solution bundle are certified for Zoom Rooms, Microsoft Teams on Android, and RingCentral Meetings Rooms (and Tencent for the China-only version). Contact the manufacturer for additional information on pending and granted certifications.</p> <p>Verified Hardware</p> <p>Biamp TesiraFORTÉ X 400</p> <p>QSC Q-SYS Core 8 Flex</p> <p>Shure IntelliMix P300</p> <p>For latest information on compatible products, contact your preferred partner.</p>	
<p>COMPUTE MOUNT</p> <p>Fits Logitech RoomMate and other compute devices with 100x100 or 75x75 VESA pattern</p> <p>Dimensions (H x W x D): 35 mm (1.38 in) x 164 mm (6.46 in) x 350 mm (13.78 in)</p>					
<p>KIT COMPONENTS</p> <p>Logitech RoomMate</p> <p>Logitech Tap IP</p> <p>Compute Mount</p>					
PACKAGE CONTENTS				PART NUMBERS	
<p>Tap IP</p> <p>Tap IP touch controller</p> <p>VESA mounting screws (4)</p> <p>Microfiber Cloth</p> <p>Documentation</p>	<p>RoomMate</p> <p>Logitech RoomMate</p> <p>Power supply</p> <p>AC cable</p> <p>VESA bracket</p> <p>Remote control</p> <p>Documentation</p>	<p>Compute Mount</p> <p>Compute Mount with Cable Retention Clamp</p> <p>Mounting Hardware</p> <p>Documentation</p>		<p>US/CA/MX: 991-000397</p> <p>Brazil: 991-000398</p> <p>Argentina/Chile: 991-000399</p> <p>EU/SEA/INDO: 991-000400</p> <p>UK/HK: 991-000401</p> <p>Switzerland: 991-000402</p> <p>AUS/NZ: 991-000403</p> <p>Taiwan: 991-000404</p> <p>India: 991-000405</p> <p>China: 991-000406</p> <p>Japan: 991-000407</p>	



Contact your reseller
or contact us at
www.logitech.com/vcsales

Logitech Americas
7700 Gateway Blvd.
Newark, CA 94560 USA

Logitech Europe S.A.
EPFL - Quartier de l'Innovation
Daniel Borel Innovation Center
CH - 1015 Lausanne

Logitech Asia Pacific Ltd.
Tel : 852-2821-5900
Fax : 852-2520-2230

© 2022 Logitech. Logitech, the Logitech logo and other Logitech marks are owned by Logitech and may be registered. All other trademarks are the properties of their respective owners. Logitech assumes no responsibility for any errors that may appear in this publication. Product, pricing and feature information contained herein is subject to change without notice.

Published September 2022